

## Guide On Loading lut On ANDYCINE A6PLUS

### **1. SD Card Format**

FAT32 and NTFS

### **2. Max Files Limit**

Maximum 8 Lut files

### **3. File Requirements**

The lut should in *.cube*

Single file not exceeded to 7.9Mb

Support LUT-3D-Size 16, 17, 32,33,64,65 the files should be valid

The files' name should in English or Arabic Words

### **4. Steps and Instruction**

Make sure that the SD card correctly insert

Enter the Monitor Menu--- "Color" --- "Load Lut"

After this, the monitor will auto detect the SD card

A. There is no SD Card

The screen will show failed, please try one more time, if not work, restart the monitor

**B. There is SD Card**

The monitor will erase the existing user's lut file and show "Initializing" .

If there is no valid lut file in SD card, the lut will not load. The monitor will show "clean up"

**C. If there is valid lut file in SD card, the monitor will load lut files and show "[n] name. The [n] shows the quantity number. The "name" should in lut files' name. If load successful, the screen will show "complete[n]" . [n] Stands for the quantity number for lut files should under "8"**

If you have question about this, please write to

[cs@andycine.com](mailto:cs@andycine.com) for help