



ShurLok II Directions For Use

The ShurLok II operates on a patented system of two groups of combinations. One combination opens the shackle (initial factory setting on 0-0-0-0) and the second combination opens the front key storage door (initial factory setting on 3-3-3-3). To change the factory default settings and set your own combination, follow the instructions below.

1. Set dials on shackle opening combination (factory setting on 0-0-0-0) and open the shackle.
2. Use a coin or paper clip to turn the change button 90 degrees (1/4 turn) clock-wise. Never force the change button. If it is difficult to turn, make sure the numbers are lined up and that you have the correct combination.
3. Set the combination to the desired shackle combination.
4. Return the change button to the original position by turning counter-clockwise 90 degrees (1/4 turn)
5. The front facing key door combination is automatically set when the new shackle combination is set. Follow the chart below to find the new combination for the front door.



NOTE: If the lock will not open the first time, simply press down on the dials to settle them in place.

Shackle to Door Conversion Chart

Shackle	0	1	2	3	4	5	6	7	8	9
Door	3	4	5	6	7	8	9	0	1	2

Example: Shackle combination 7724 – The door combination would then be 0057

Example: Door combination 8143 – The shackle combination would then be 5810

The ShurLok Zero Locking Feature

The ShurLok can be opened in the dark or by the vision-impaired by following the below directions:

1. Roll all numbers on the dials up and away from you. By doing so, the dials will all stop on zero.
2. Count the clicks up to your combination (Hint: if you will be using this feature often, we recommend setting your combination to lower numbers that are easier to count up to)

Need Help? Before calling, visit: www.shurlok-products.com/lockbox-4.htm

FJM Security
18424 HWY 99
Lynnwood, WA 98037

www.fjmsecurity.com
Patent Pending