


zmodo™




Mini WiFi Camera

Quick Start Guide




VER-Z3

1 Getting to know your camera




- ① Status Light
- ② Infrared (IR) LED
- ③ HD Camera
- ④ Light Sensor
- ⑤ Microphone



- ⑥ Reset Pinhole
- ⑦ Speaker
- ⑧ Adjustable Stand
- ⑨ Power Port

To reset the camera, use a pin or a thin object to press and hold the reset pin on the back of the camera for 10 seconds. The LED Status Light turn off, and start blinking green when the camera is ready to be set up again.

What's in the box:




Camera



Screws & anchors (x3)



Mounting bracket



Power adapter



Quick guide

2 Welcome!

This quick start guide will help you configure your Mini WiFi camera for initial use. For detailed instructions and troubleshooting, please visit:

www.zmodo.com/support

Before you begin:

- Make sure that you have a strong WiFi connection at the location of your camera. Visit www.zmodo.com/support for advice on improving your WiFi signal range.
- Make sure you know the SSID (WiFi network name) and password of the **2.4GHz WPA/WPA2 WiFi network** that you want your camera to connect to. Your network cannot be hidden.
- Download and install the “Zmodo” app from Google Play™ or the App Store™ (*compatibility: iOS® 7.0+ or Android™ 4.0+*). Launch the app and sign up for a free Zmodo account. All of your devices will be bound to this account.



Zmodo



- Power on your camera with the supplied power adapter.



We are constantly working to improve our product and app. Please visit www.zmodo.com/support for updated instructions, manuals, and more.




This device can be set up with a Zmodo Beam. If you own a Beam, please follow the instructions in your Beam quick guide to connect your device instead.

1



Log in and select the Add Device **+** option in the upper right corner.



2



Select the “Zink” connection method to connect your camera. Your camera will be added to your Zmodo account.

3



Tap  to proceed (if you're setting up multiple cameras at once, tap  to add additional units).

4



Follow the on-screen instructions and select “Tap here to begin setup” to go to the WiFi settings page on your smartphone.

5



Select the network named “ZMD_SAP” and connect to it.


6



Return to the Zmodo app page and enter the name and password of the WiFi network that you want your camera to connect to. Note: the WiFi name and password are case-sensitive.

Tap  to proceed.


7



If you see this screen, the app will connect your camera to your WiFi network. This may take a few minutes. Once it's completed, please skip to step 11.

If you do not see this screen, please proceed to step 8.

8




If this app interface appears, please press "Tap here to select WiFi".

9




Select the WiFi network that your camera will connect to, and connect to it. Return to the Zmodo app once your mobile device is connected to the WiFi network.


10



The app will automatically search for your camera and connect it to the WiFi network. This may take a few minutes.

11



Name your camera and set a password for it. Tap  to proceed.

Note: The password provides an additional layer of security for your devices. You will not need to use this password when accessing your devices from the Zmodo app. It is not required, but it is highly recommended.


12




Your camera has been successfully configured! You can now share or view your camera.

3 Mounting your cameras (optional)


- 1 Locate the mounting plate in the packaging. You may need to remove the mounting plate by pushing the tabs in with your thumb and separating the mounting plate from the bracket as shown below.




- 2 Line the mounting plate against the wall and mark the appropriate holes. Drill three holes slightly smaller than the provided wall anchors and use a hammer to gently insert the anchors into the wall. The tip of the anchors should be flush against the wall. Fasten the three screws through the holes on the mounting bracket and the anchors as shown.



- 3 Take the camera with the bracket (as shown) and attach it to the mounting plate. You can rotate the bracket to adjust the camera for a better viewing angle.



- 4 Connect the supplied power adapter to the power port on the camera, and plug the adapter into a nearby power outlet. The LED light will light up when it powers on.



4 Recording and Viewing Options

Recording Options

This device is compatible with the upcoming cloud services. Please visit www.zmodo.com/support for release information and more updates. The cloud service will allow you to:

- Record continuously and store the footage on our secure cloud servers.
- Create and save video clips from your recordings.
- Access your footage and clips at any time from any location.
- Enjoy more smart features in the future.

Viewing Options

All of your Zmodo devices will be bound to your Zmodo user account. You can access your camera and other devices by using the Zmodo app with any Android™ or iOS® device. Just download the Zmodo app from Google Play™ or the App Store™.

You can also access your devices from any web browser with our web app. Visit user.zmodo.com and log in with your Zmodo user account information.

5 Status Light Definitions

Solid green

The camera is powering on.

Blinking green

The camera is ready for setup.

Blinking blue

The camera is connecting to the WiFi network. Please do NOT turn off or unplug the camera at this time.

Solid blue

The camera has successfully connected to the WiFi network.

If you were unable to connect your camera successfully:

- Make sure that you are connecting to a **2.4GHz WPA/WPA2 WiFi network**, and that your network is not hidden.
- Please make sure that you entered the network name and password correctly. *Note: Both are case-sensitive.*
- You may need to improve your WiFi strength. Visit www.zmodo.com/support for suggestions.
- Try resetting your camera by pressing and holding the reset pin on the bottom for 10 seconds until the Status Light turns off. Retry the setup process when the LED is blinking green.

6 Support

Having difficulty?

You can use the Live Chat function in Zmodo app if you have any technical problems.

Please follow the steps below:

Swipe to the right in Zmodo app, and select Live Chat under "Support".

For more instructions, troubleshooting, support, and other resources, please visit:

www.zmodo.com/support



Like us on Facebook.com/Zmodo
Scan the QR-code below!



Follow us on Twitter @Zmodo
Scan the QR-code below!



Android is a trademark of Google Inc. Google Play is a trademark of Google Inc. Apple, the Apple logo, and iPhone are trademarks of Apple Inc., registered in the U.S. and other countries. Apple Store is a service mark of Apple Inc.